

2-inch exit ferrite magnet compression driver

- 800Hz recommended min. crossover freq (12dB/oct)
- Single piece titanium diaphragm and surround

200W

Continuous  
power rating

107dB

sensitivity

3in

Edgewound clad  
copper voice  
aluminium coil

General Specifications

|                                        |                                 |
|----------------------------------------|---------------------------------|
| Power Rating                           | 100W                            |
| Continuous power rating                | 200W                            |
| Rated impedance                        | 8 ohm                           |
| Sensitivity                            | 107dB                           |
| Frequency range                        | 500-18,000Hz                    |
| Recommended min. crossover (12 dB/oct) | 800Hz                           |
| Magnet type                            | Ferrite                         |
| Voice coil diameter                    | 75mm / 3in                      |
| Voice coil material                    | Edgewound copper clad aluminium |
| Diaphragm material                     | Titanium                        |
| Surround material                      | Titanium                        |

Mounting Information

|             |                                        |
|-------------|----------------------------------------|
| Width       | 180mm / 7.0in                          |
| Depth       | 68.0mm / 2.7in                         |
| Fitting     | Bolt (4 x M6 holes on a 102mm/4in PCD) |
| Throat exit | 50mm / 2in                             |
| Unit weight | 4.9kg / 10.8lb                         |

Packed Dimensions & Weight

|                            |                                              |
|----------------------------|----------------------------------------------|
| Single pack size W x D x H | 214mm x 196mm x 82mm / x 8.4in 7.7in x 3.2in |
| Single pack weight         | 5.1kg / 11.2lb                               |

Repair kits

|       |                            |
|-------|----------------------------|
| T6509 | Diaphragm repair kit 8 ohm |
|-------|----------------------------|

Frequency Response and Impedance Curves

